

**- Universal Remote (X-10 PRO PUR08) -
- Remote Arming / Light Control -**

Objective

Arm to Home mode and turn on a light with the X-10 PRO Universal Remote Control (PUR08).

Equipment List

- ◆ Apex Destiny 6100 control panel, rev. 8.05 or greater
- ◆ X-10 PRO Power Line Interface Module, PSC05
- ◆ X-10 PRO Incandescent Wall Switch Module, PLW01
- ◆ X-10 PRO Transceiver / Appliance Module, PAT01
- ◆ X-10 PRO Universal Remote Control, PUR08

The PUR08 Universal Remote provides convenience in arming the control, turning on/off the TV/VCR and controlling lights, all from one hand-held remote.

Sequence of Operation

Pressing the X-10 button on the PUR08 followed by a 01 and the channel (+) button will arm the system to Home and turn on an X-10 controlled light. Pressing the X-10 button on the PUR08 followed by 02 and the channel (+) button will only turn on the X-10 controlled light. Pressing the channel (-) button will turn the light off.

System Sequence of Events

- 1) When the PUR08 X-10 button is pressed followed by 01 and the channel (+) button it transmits X-10 input signal 1 "A1 ON" which causes the system to arm to Home and also causes the system to send an "ON" command to Control Channel 1.
- 2) Control Channel 1 transmits X-10 output signal "A2 ON" that turns on the X-10 light.
- 3) When the PUR08 X-10 button is pressed followed by 02 and the channel (+) button it transmits X-10 output signal "A2 ON" which turns on the X-10 light.
- 4) Pressing the channel (-) button transmits X-10 output signal "A2 OFF" that turns the light off.

Required Programming

Location	Value	Function
9940	01	Zone type = 015, Option 1 = 000, Option 2 = 001, Hardware device = 020, Input = 1
5570	096	X-10 input house code / unit assignment (A1)
5572	019	X-10 input "ON" button function assignment – Arm to Home
4097	001	Enable control channel 1
4118	097	X-10 output signal "A2"
0193	001	System trigger – Arm to Home

Application Diagram

